## **TK102-2 (Xexun)**

Time zone = UTC		NOTE
Example	time zone+password+space+UTC	UTC/GMT - Coordinated Universal Time
SMS	time zone123456 0	It is necessary to set UTC. GetPosition server is
Reply	time zone ok!	responsible for setting correct time for your application.
APN		
Example	apn+password+space+ APN's Name	APN (access point name) – it depends on your provider
SMS	apn123456 internet	of SIM card
Reply	apn ok!	
IP or DNS and Port		
Example	adminip+password+space+DNS+space+port	Please use DNS = gps.getposition.eu for our server and
SMS	adminip123456 gps.getposition.eu 9003	port 9003 for TK102-2
Reply	adminip ok!	
Tracking interval		
Example	t+time+***n+password	005s – tracking interval is 5 seconds
SMS	t005s***n123456	
Reply	t005s***n ok!	